



C26

Type Size: S1

Classification Contact: Rigid contact bridge

Classification Contact Mat: Silver

Classification Terminal: Screw terminal

Sample image

IEC 60947-3 EN 60947-3, VDE 0660 Teil 107

Rated insulation voltage U_i

Voltage (V)	AC / DC
690	AC

Rated impulse withstand voltage U_{imp}

Voltage (kV)	Overvoltage category	Pollution degree	Supply system	Function
6	III	3	Valid for lines with grounded common neutral termination	switch

Rated uninterrupted current I_u/l_{th}

Current (A)	Ambient temperature (°C)	Peak temperature (°C)	additional requirements
32	55	60	Ambient temperature +55°C during 24 hours with peaks up to +60°C

Conventional enclosed thermal current I_{the}

Current (A)	Ambient temperature (°C)	Peak temperature (°C)	Additional requirements	No. of stages (from - to)	Mounting	Mounting size
32	35	40	Ambient temperature +35°C during 24 hours with peaks up to +40°C	--	--	--

Rated operational current I_e

Utilization category	Voltage (V)	Current (A)
AC-15	220 - 240	14
AC-15	380 - 440	6
AC-20A	690	32
AC-21A	20 - 690	32
AC-22A	220 - 500	32
AC-22A	660 - 690	32

Rated operational power

Utilization category	Voltage (V)	No. of phases	No. of poles	Power (kW)
AC-2	220 - 240	3	3	8
AC-2	380 - 440	3	3	15
AC-2	500 - 500	3	3	18,50
AC-2	660 - 690	3	3	15
AC-3	220 - 240	3	3	5,50
AC-3	380 - 440	3	3	11
AC-3	500 - 500	3	3	11
AC-3	660 - 690	3	3	11
AC-3	110 - 120	1	2	2,20
AC-3	220 - 240	1	2	4
AC-3	380 - 440	1	2	5,50
AC-4	220 - 240	3	3	2,70
AC-4	380 - 440	3	3	5,50
AC-4	500 - 500	3	3	5,50
AC-4	660 - 690	3	3	5,50
AC-4	110 - 120	1	2	0,75
AC-4	220 - 240	1	2	1,50
AC-4	380 - 440	1	2	3
AC-23A	220 - 240	3	3	7,50
AC-23A	380 - 440	3	3	15
AC-23A	500 - 500	3	3	15
AC-23A	660 - 690	3	3	15
AC-23A	110 - 120	1	2	2,20

Rated operational power				
Utilization category	Voltage (V)	No. of phases	No. of poles	Power (kW)
AC-23A	220 - 240	1	2	4
AC-23A	380 - 440	1	2	7,50

Max Fuse Rating IEC		
Fuse characteristic	Numb Fuses	Current (A)
gG	1	50

UL60947-4-1 , UL508

Rated insulation voltage Ui		
Voltage (V)	AC / DC	
600	AC	

Rated thermal current			
Current (A)	Ambient temperature (°C)	Additional Text	
40	0 - 40	-	

CSA

Rated insulation voltage Ui		
Voltage (V)	AC / DC	
600	AC	

Rated thermal current			
Current (A)	Ambient temperature (°C)	Additional Text	
40	0 - 40	-	

GENERAL TECHNICAL INFORMATION

Tightening torque of screws		
tightening torque (Nm)	tightening torque (lb-in)	
1,30	12	

Rated short-time withstand current Icw	
Time (s)	Current (A)
1	350

Size of conductor					
composition of conductor	Min. / Max. value	No. of conductor per terminal	Cross section (mm ²) or (AWG/kcmil)	Material of the wire	
solid wire	Min.	1	1mm ²	Copper	
solid wire	Min.	2	1mm ²	Copper	
flexible wire	Max.	2	6mm ²	Copper	
flexible wire	Max.	2	AWG 10	Copper	
flexible wire	Min.	1	1.5mm ²	Copper	
flexible wire	Min.	2	1.5mm ²	Copper	
Single-core or stranded wire	Max.	2	6mm ²	Copper	
Single-core or stranded wire	Max.	2	AWG 8	Copper	
flexible wire with ferrule according to DIN 46228	Max.	2	4mm ²	Copper	
flexible wire with ferrule according to DIN 46228	Min.	1	1mm ²	Copper	
flexible wire with ferrule according to DIN 46228	Min.	2	1mm ²	Copper	

Approbations	
Specification	Marking

EAC



CE marking



IEC 60947-3; EN 60947-3; VDE 0660 Teil107

**IEC 60947-3
EN 60947-3**

UL 60947-4-1; CSA C22.2 No. 60947-4-1



CSA C.22.2 No.14



GB/T14048.3


Power loss per pole
Power (W)

1,30

Conditions during transport and storing		
<i>Minimum temperature (°C)</i>	<i>Maximum temperature (°C)</i>	<i>additional requirements</i>
-40	85	In case of temperatures below -5°C no shock load permissible
Shock / Vibration		
<i>Type of oscillation</i>	<i>Values</i>	
Resistance to vibration	Min. 4g, 2-100Hz, 1,6mm	
Resistance to shock	Min. 5g, 6ms	
General Information		
<i>Text</i>		
<ul style="list-style-type: none"> - Do not lubricate or treat contacts. - Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology. - Use copper wire only. Do not coat the wire end with tin. - Terminals with factory fitted jumper links are tightened during production. Take care during installation to ensure factory fitted links are not lost by undoing both sides of linked terminals. After wiring, all terminal screws must be tightened to recommended torque specifications. - Use only fully insulated cable lugs resp. FASTON receptacles. - After installation of the switches the spacings between the terminals must be sufficient to fulfill the requirement of the applicable standards. 		
Operating temperature		
<i>Min. Temperature [°C]</i>	<i>Max. Temperature [°C]</i>	
-25	60	